


Technical Information


Mounting instructions TR-Encoder Ø 58 / Ø 65 Draw-Wire-Box (Rope length transmitter)





Pos.	Parts List	Pos.	Parts List
Α	Cable traction box	С	Encoder which can be mounted
В	Accessories, Scope of delivery	D	Auxiliary material: Mounting gage, no scope of delivery

Pos. B, Accessories	Pos. D, Auxiliary material (no scope of delivery)
 O-ring 3 x Cheese-head screws M4x8 Clutch disc Clutch disc for shaft flange connection Hex key, wrench size = 1.3 mm 	 Mounting gage for rope length transmitter TR designation: ZN 00-000-1857 Hex key, wrench size = 3 mm



TR - ELECTRONIC GmbH, Eglishalde 6, 78647 Trossingen, Tel. ++49 (0)7425 / 228-0, Fax ++49 (0)7425 / 228-33 + 449 (0)7425 / 228-32 + 449 (0)7425 / 228-228 / 228 / 228 / 228 / 228 / 228 / 228 / 228 / 228 / 228 / 228 / 228 / 228 / 228 / 228 / 228 / 2

Subject to change



Technical Information

Mounting step 3



Attach mounting gage to the encoder:

→ With the mounting gage the clutch disc will be positioned onto the measure 2.8^{+0.1} (see figure).

With the hex key and the aid of the two setscrews M2.5x5 the clutch disc is mounted onto the encoder shaft.

Remove mounting gage.

Mounting step 4




Fasten mounting flange, on the side of the O-ring, with the encoder. For this purpose the three cheese-head screws M4x8 should be used.

CAUTION!

The screws must be secured with Loctite 241 Cat.No 24112.

Mounting step 5



Insert clutch disc onto the housing of the cable traction box. Place encoder with flange ring and clutch disc onto the O-ring of the cable traction box housing.

CAUTION!

Pull easily on the cable traction, until the clutch disc engages. Only in this way the encoder / mounting flange lies flatly onto the housing of the cable traction box.

Rotate encoder connection into the desired direction.

Mounting step 6



Fasten mounting brackets at the housing of the cable traction box. For this purpose the four counter-sunk screws M4x8 should be used.

Subject to change

CAUTION!

The screws must be secured with Loctite 241 Cat.No 24112.

 $\textbf{TR - ELECTRONIC GmbH}, Eglishalde \ 6, \ 78647 \ Trossingen, \ Tel. \ ++49 \ (0)7425 \ / \ 228-0, \ Fax \ ++49 \ (0)7425 \ / \ 228-33$